



SENNHEISER

823 - 865 MHz

Frequenzbereich E / Frequency range E

**Zusatzinformationen für Systeme der Serie
evolution wireless IEM G4**

**Additional information for Sennheiser
evolution wireless IEM G4 systems**

DE

Für die Übertragung steht Ihnen folgender Frequenzbereich zur Verfügung:

Frequenzbereich	Bandbreite	Anzahl Frequenzen
823 - 865 MHz	42 MHz	max. 1680

Die Sender und Empfänger verfügen über jeweils 20 Kanalbänke, auf denen werksseitig Frequenz-Presets voreingestellt sind. Innerhalb einer Kanalbank sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In den Kanalbänken **U1 bis U6** können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Umständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken **1 bis 20** sind in der Tabelle auf der folgenden Seite dargestellt.

Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen

In Ihrem Land gelten möglicherweise gesonderte Rahmenbedingungen und Einschränkungen für die Nutzung von Frequenzen.

Informieren Sie sich vor der Inbetriebnahme des Produktes unter folgender Adresse:

www.sennheiser.com/frequency-information

EN

Transmitters and receivers are available in the following frequency range:

Frequency range	Bandwidth	Number of frequencies
823 - 865 MHz	42 MHz	max. 1680

Transmitters and receivers have 20 frequency banks respectively. Each of the channels in the frequency banks has been factory-preset to a frequency. These frequency presets within one frequency bank are intermodulation-free. They cannot be changed.

The frequency banks **U1 to U6** allow the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation free.

The table printed on the following page lists the frequency presets in the frequency banks **1 to 20**.

Conditions and restrictions for using frequencies

There may be special conditions and restrictions for using frequencies in your country.

Before putting the product into operation, find the information for your country at the following address:

www.sennheiser.com/frequency-information

Sennheiser electronic GmbH & Co. KG

Am Labor 1, 30900 Wedemark, Germany, www.sennheiser.com
Publ. 01/18, 578641/A01

Frequenzbereich E / Frequency range E: 823 - 865 MHz

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10
1	823.100	831.900	823.100	823.200	863.100	826.100	826.200	823.200	830.200	838.200
2	823.500	830.400	823.500	823.600	863.500	826.500	826.600	823.600	830.600	838.600
3	824.100	829.900	824.900	825.000	864.100	827.200	827.300	824.150	831.150	839.150
4	825.500	829.100	826.900	827.000	864.900	828.100	828.200	824.850	831.850	839.850
5	827.700	828.500	828.100	828.200	823.100	829.400	829.500	825.350	832.300	840.300
6	828.900	828.100	831.050	831.150	824.300	830.400	830.500	826.250	832.900	840.900
7	830.700	826.000	863.600	863.700	825.900	831.200	831.300	826.850	833.650	841.650
8	831.500	824.800	864.450	864.550	827.900	831.800	831.900	827.850	835.800	843.800
9	863.100	823.100	824.100	824.200	830.100	863.100	863.200	838.200	846.200	854.200
10	864.700	863.100	825.350	825.450	823.600	863.600	863.700	838.650	846.700	854.700
11		863.800	826.000	826.100	829.200	864.800	864.900	839.300	847.500	855.500
12		864.700	830.500	830.600	831.800	824.600	824.700	840.100	848.150	856.150
13			831.800	831.900				842.150	849.050	857.050
14			863.100	863.200				843.500	850.900	858.900
15								844.550	852.400	860.400
16								845.300	853.500	861.500

Channel	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20
1	823.200	830.200	823.200	830.200	838.200	846.200	830.100	838.100	846.100	854.100
2	823.600	830.600	823.600	830.600	838.600	846.600	830.500	838.500	846.500	854.500
3	824.150	831.150	824.200	831.200	839.200	847.200	831.300	839.300	847.300	855.300
4	824.850	831.850	825.000	832.000	840.000	848.000	833.300	841.300	849.300	857.300
5	825.350	832.300	826.600	833.200	841.200	849.200	833.900	841.900	849.900	857.900
6	826.250	832.900	827.800	834.800	842.800	850.800	835.500	843.500	851.500	859.500
7	826.850	833.650	829.800	838.600	846.600	854.600	836.900	844.900	852.900	860.900
8	827.850	835.800	838.300	839.900	847.900	855.900	837.900	845.900	853.900	861.900
9	846.200	854.200	838.800	842.600	850.600	858.600	825.300	823.300	823.100	823.100
10	846.650	854.700	840.500	843.100	851.100	859.100	846.700	828.500	828.300	824.900
11	847.300	855.500	841.400	844.800	852.800	860.800	851.100	850.700	830.100	829.300
12	848.100	856.150	844.300	845.500	853.500	861.500	857.300	855.100	837.700	836.300
13	850.400	857.050	845.800				863.100	863.100	860.100	843.500
14	851.250	858.900	854.200				864.900	864.900	864.900	849.300
15	852.950	860.400	860.000				831.800	839.800	847.800	855.800
16	853.700	861.500	861.100				842.800	857.600	824.200	832.200